偏心角度转换器 ANGLE CONVERTER


在旋转冲击运动时如果偏心角度超过3°，会对活塞杆造成很高的偏心冲击力，使轴承磨损加剧，易导致活塞杆受损变形弯曲，缓冲器寿命快速减少。

PRTA偏心角度转换器提供了使缓冲器可以长久持续使用的解决方案；实践证明，使用偏心角度转换器最大偏心角度达25°

注：偏心角度转换器只能装到没有冲击头的活塞杆上面。

when it sport with rotary percussive,if the eccentric angle more than 3°,It has big shock to piston rod,the bearing will wear serious.piston rod easy to be out of shape and curved,the lifetime of absorber will short.PRTA switcher can make the absorber lifetime much longer in long time. practice has proved that if use our switch,the max eccentric angle can be 25°.

Remark: this switch only can fix in piston rod which without shock head.



型号 Model	行程 Stroke (mm)	A	B	C	D	E	F	G	H
SCL1410	10	34	18	9	8	M14×1.5	M14×1.5	19	17
SCL1415	15	39	23	12	8	M14×1.5	M14×1.5	19	17
SCL2016	16	48	28	12	12	M20×1.5	M20×1.5	25	22
SCL2020	20	51	31	15	12	M20×1.5	M20×1.5	25	22
SCL2525	25	62	40	14	16	M25×1.5	M25×1.5	35	31
SCL2725	25	62	40	14	16	M27×1.5	M27×1.5	35	31
SCL2725B	25	62	40	14	16	M27×3.0	M27×3.0	35	31
SCL3325	25	69	47	15	20	M33×1.5	M33×1.5	45	40
SCL3625	25	69	47	15	20	M36×1.5	M36×1.5	45	40

